

How Fast Can Quantum Annealers Count?

Itay Hen^{1,2,*}

¹Quantum Laboratory, Applied Physics Center, NASA Ames Research Center, Moffett Field, California 94035, USA

²Department of Physics, University of California, Santa Cruz, California 95064, USA

(Dated: January 22, 2013)

We outline an algorithm for an efficient solution of the Quantum Counting problem using Adiabatic Quantum Computation (AQC). We show that using local adiabatic evolution, a process in which the adiabatic procedure is performed at a variable rate, the problem is solved as efficiently as the analogous circuit-based algorithm, i.e., quadratically faster than the corresponding classical algorithm. The above algorithm provides further evidence for the potentially powerful capabilities of AQC as a paradigm for efficient problem solving on a quantum computer. We also discuss the algorithm in relation to the problem of Quantum Phase Detection.

PACS numbers: 03.67.Ac, 03.67.Lx, 89.70.+c

Keywords: Adiabatic quantum computing, Quantum annealers, Grover's search algorithm, Quantum counting, Phase detection

I. INTRODUCTION

The paradigm of Adiabatic Quantum Computation (AQC), proposed by Farhi *et al.* [1] about a decade ago is a simple yet intriguing approach to problem solving on a quantum computer. Unlike the leading paradigm of circuit-based quantum computing, AQC is an analog, time-continuous method which does not require the design and use of quantum gates. As such, it can in many ways be thought of as a simpler and perhaps more profound method for performing quantum computations while also being easier to design and implement experimentally [2, 3].

The potential advantages of AQC over the usual circuit-based and other computation paradigms have naturally generated substantial research, and intensive efforts have been made towards finding computational problems that are solved more efficiently on an adiabatic quantum computer (henceforth, a quantum annealer) than on a classical computer (see, e.g., Refs. [4–12] and references therein). One of the most important results in that context, which serves as an additional indication to the potential capabilities of the AQC paradigm, is the existence of a theorem stating that adiabatic quantum computing is polynomially equivalent to circuit model quantum computation [13, 14].

Despite the above equivalence, it is not yet understood in which cases adiabatic quantum computation is just as efficient as circuit model quantum computation (or even potentially polynomially more efficient). It has therefore become of great interest to look at problems for which circuit model algorithms are known, and to see whether equally-efficient adiabatic algorithms can be found. To date, however, there are almost no examples to show that AQC is as efficient as the circuit-model paradigm. One notable exception is the adiabatic Grover's search algo-

rithm devised by Roland and Cerf [15], demonstrating that the quadratic speed-up over classical algorithms first shown by Grover [16] using circuit-based computation, can also be gained with adiabatic quantum algorithms (we discuss the algorithm in more detail later).

In what follows, we consider another problem for which, much like Grover's search problem, there is a circuit-model algorithm that is quadratically faster than its classical counterpart. This is the problem of 'Quantum Counting' [17, 18] in which one has to estimate the number of occurrences of a specific item in an unsorted database. We show that the Quantum Counting problem may also be solved on a quantum annealer in an efficient manner via the use of Local Adiabatic Evolution (LAE) [15]. We shall see that the efficiency of the proposed method is on par with the analogous circuit-based algorithm and so is quadratically faster than the corresponding classical algorithm.

The paper is organized as follows. In the next section we briefly discuss the principles of the Quantum Adiabatic Algorithm that is the heart of AQC. We then describe in some detail the concept of Local Adiabatic Evolution (LAE) in Sec. III. In Sec. IV, we analyze the dynamical equations of the QAA for the adiabatic Grover's algorithm. These are later used in Sections V and VI to devise an efficient quantum-adiabatic algorithm for solving the problem of Quantum Counting. In Sec. VII we briefly discuss the suggested algorithm in the context of quantum phase detection, and finally, in Sec. VIII, we conclude with a few comments.

II. QUANTUM ADIABATIC ALGORITHM (QAA)

We first describe the Quantum Adiabatic Algorithm (QAA) which provides the general approach for solving problems by casting them in the form of optimization problems [1].

Within the framework of the QAA approach, the solu-

*Electronic address: itay.hen@nasa.gov

tion to an optimization problem is encoded in the ground state of a Hamiltonian $\hat{H}_p$. To find the solution, the QAA prescribes the following course of action. As a first step, the system is prepared in the ground state of another Hamiltonian $\hat{H}_d$, commonly referred to as the driver Hamiltonian. The driver Hamiltonian is chosen such that it does not commute with the problem Hamiltonian and has a ground state that is fairly easy to prepare. As a next step, the Hamiltonian of the system is slowly modified from $\hat{H}_d$ to $\hat{H}_p$, using the linear interpolation, i.e.,

$$\hat{H}(s) = s\hat{H}_p + (1-s)\hat{H}_d, \quad (1)$$

where $s(t)$ is a parameter varying smoothly with time, from 0 at $t = 0$ to 1 at the end of the algorithm, at $t = \mathcal{T}$. If this process is done slowly enough, the adiabatic theorem of Quantum Mechanics (see, e.g., Refs. [19] and [20]) ensures that the system will stay close to the ground state of the instantaneous Hamiltonian throughout the evolution, so that the system finally arrives at a state that is close to the ground state of $\hat{H}_p$. At this point, measuring the state will give the solution of the original problem with high probability.

In the simple case where $s(t)$ varies from zero to one at a constant rate, the runtime $\mathcal{T}$ must be chosen to be large enough so that the adiabatic approximation holds: this condition determines the efficiency, or complexity, of the QAA. A condition on $\mathcal{T}$ can be given in terms of the instantaneous eigenstates $\{|m\rangle\}$ and eigenvalues $\{E_m\}$ of the Hamiltonian $H(s)$, as [5, 21]

$$\mathcal{T} > \frac{1}{\epsilon} \frac{\max_s V_{01}(s)}{\min_s g^2(s)}, \quad (2)$$

where ϵ is a small number, inversely proportional to the running time of the algorithm, that controls the expected probability for failure of the algorithm, $g(s)$ is the first excitation gap $E_1(s) - E_0(s)$ and $V_{01}(s) = |\langle 0 | dH/ds | 1 \rangle|$ (in our units $\hbar = 1$).

III. LOCAL ADIABATIC EVOLUTION

As is well established by now, LAE can provide a significant speed-up in calculation times if one utilizes the concept of ‘Local Adiabatic Evolution’ (LAE), in the framework of which the adiabatic parameter $s(t)$ is varied not at a constant rate but rather at a variable rate, slowing down in the vicinity of the minimum gap and speeding-up in places where the gap is large [15]. The procedure is based on formulating a ‘local’ Landau-Zener condition for each value of the adiabatic parameter s . This condition can be written as:

$$\left| \frac{ds}{dt} \right| \leq \epsilon \frac{g^2(s)}{V_{01}(s)}, \quad (3)$$

where $g(s)$, $V_{01}(s)$ and ϵ are as in Eq. (2).

One example in which one may utilize the concept of LAE and which in turn demonstrates the potentially powerful capabilities of Adiabatic Quantum Computation was first illustrated by Roland and Cerf [15, 22]. In this example, an efficient adiabatic algorithm for solving Grover’s search problem [16] which describes a search for a marked item in an unstructured database, is found. More specifically, Roland and Cerf showed that while the application of the adiabatic theorem with a linear $s(t)$ results in a running time that is of order $N - N$ being the number of items in the database – a carefully chosen variable rate of $s(t)$ yields a running time that scales like $\sqrt{N}$, i.e., a quadratic speed-up is gained, similarly to the original result by Grover, that was found for the circuit-based model.

LAE however can only be efficiently used in cases where one has proper knowledge of the exact behavior of the gap and relevant matrix elements of the system for the problem at hand. This is normally not the case. The amenability of Grover’s search problem to LAE stems from the fact that the gap of the system (as well as the relevant matrix element) can be calculated explicitly beforehand, even if the specific ground state is not known. With a proper choice of problem and driver Hamiltonians (which are discussed next), the gap in the Grover search problem is given by the simple expression:

$$g(\eta; s) = \sqrt{1 - 4(1 - \eta)s(1 - s)}, \quad (4)$$

where $\eta = M/N$ is the ratio of the number of solutions M to the size of the database N . Moreover, the matrix element $\left| \left\langle d\hat{H}/ds \right\rangle \right|$ can also be calculated in a straightforward manner to give:

$$V_{01}(s) = \left| \left\langle 0 \left| d\hat{H}/ds \right| 1 \right\rangle \right| = \frac{\sqrt{\eta(1 - \eta)}}{g(\eta; s)} \quad (5)$$

The condition for local adiabatic evolution for the Grover problem is thus simply given by:

$$\left| \frac{ds}{dt} \right| \leq \epsilon \frac{g^3(\eta; s)}{\sqrt{\eta(1 - \eta)}}, \quad (6)$$

A less strict inequality using the fact that $V_{01}(s) < 1$ yields the more convenient bound of [15]:

$$\left| \frac{ds}{dt} \right| \leq \epsilon g^2(\eta; s). \quad (7)$$

Integrating in time either of the two equations above between $t = 0$ (also, $s = 0$) and $t = \mathcal{T}$ ($s=1$) yields immediately:

$$\mathcal{T} \propto \frac{1}{\epsilon} \sqrt{N/M} = \frac{1}{\epsilon \sqrt{\eta}} \quad (8)$$

in the limit of $N \rightarrow \infty$, i.e., a quadratic speed-up over any classical search algorithm, a result also shared by Grover’s original circuit-based algorithm [16].

IV. ANALYSIS OF THE ADIABATIC GROVER PROBLEM

An important property of the gap of Grover's search problem, Eq. (4), may be formulated as follows.

$$g(\eta_1; s) \leq g(\eta_2; s) \quad \text{for any } \eta_1 \leq \eta_2, \quad (9)$$

where η_1 and η_2 are two arbitrary ratios. The above property leads to the interesting (and somewhat surprising) attractive feature of LAE for the Grover search problem: If one runs the algorithm as if the ratio of solutions is η_* even though the actual ratio of solutions η may not be known, then one still obtains at the end of the adiabatic run a state that is very close the symmetric superposition of all solution states, as long as $\eta_* \leq \eta$. This is because choosing the adiabatic profile with η_* , namely,

$$\frac{ds}{dt} = \epsilon g^2(\eta_*; s), \quad (10)$$

also satisfies the inequality Eq. (7) for any $\eta_* \leq \eta$.

The above feature is to be contrasted with the circuit-based Grover's search algorithm, in which case one must know in advance the number of solutions in order to obtain a solution to the problem with a very high probability. Within the circuit model, the problem of not knowing the number of solutions is resolved by a preliminary application of a different algorithm known as Quantum Counting designed to estimate the number of solutions M prior to the application of Grover's search algorithm.

In what follows we show that LAE, with the aid of the unique properties of the adiabatic Grover's problem presented above, may be used to solve adiabatically the problem of Quantum Counting, i.e., the problem of estimating the number M of occurrences of a specific item within an unsorted database of size N .

Before doing so however, we first analyze in some detail the dynamics of the adiabatic algorithm for Grover's search problem (a similar derivation is briefly discussed in Ref. [15]). Specifically, we derive here the equations describing an unsorted-database search with an unknown number (equivalently, ratio) of solutions M (or η) using an adiabatic profile $s(t)$ with a ratio η_* . We then calculate the probability of ending up in a solution state in two limiting cases.

A. Dynamics of the Grover-adiabatic problem

Consider the problem Hamiltonian for the Grover problem [15]:

$$\hat{H}_p = 1 - \sum_{m \in \mathcal{M}} |m\rangle\langle m|. \quad (11)$$

Here the M states $m \in \mathcal{M}$ are eigenstates of the computational basis with eigenvalue zero (all other states have eigenvalue one). The problem Hamiltonian is therefore a

diagonal matrix of size N with M zero entries and $N - M$ entries of one along the diagonal. The driver Hamiltonian is simply given by:

$$\hat{H}_d = -|\phi\rangle\langle\phi|, \quad (12)$$

where $|\phi\rangle$ is the fully-symmetric state:

$$|\phi\rangle = \frac{1}{\sqrt{N}} \sum_{i=1}^N |i\rangle. \quad (13)$$

Obviously, the ground-state of the driver Hamiltonian, i.e., the state that the system is prepared in for the adiabatic evolution, is

$$|\psi(t=0)\rangle = |\phi\rangle. \quad (14)$$

Applying the Schrödinger equation

$$i \frac{d}{dt} |\psi(t)\rangle = \hat{H} |\psi(t)\rangle \quad (15)$$

to $|\psi(t)\rangle = (c_0(t), c_1(t), \dots, c_i(t), \dots, c_N(t))$ simplifies greatly due to symmetry considerations: The state of the system has only two distinct amplitudes. The amplitudes $c_i(t)$ that correspond to 'solution' states and those that correspond to 'non-solution' states. Let us denote the former set by $a(t)$ and that of the latter by $b(t)$. The Schrödinger equation thus becomes the two coupled equations:

$$i\dot{a} = -(1-s)[\eta a + (1-\eta)b] \quad (16)$$

$$i\dot{b} = -(1-s)[\eta a + (1-\eta)b] + sb, \quad (17)$$

Note that N , the size of the problem and M , the number of solutions appear in the equations only as the ratio $\eta = M/N$.

The time-dependence of a and b is easily transformed into s dependence (as there is a one-to-one correspondence between the two in our case). The time-derivative transforms in the usual way: $d/dt = (ds/dt) \times d/ds$, and the two coupled equations now become:

$$i\epsilon g^2(\eta_*; s) a' = -(1-s)[\eta a + (1-\eta)b] \quad (18)$$

$$i\epsilon g^2(\eta_*; s) b' = -(1-s)[\eta a + (1-\eta)b] + sb. \quad (19)$$

Here, the prime symbol ($'$) stands for differentiation with respect to the new independent variable s and we have used Eq. (10) for ds/dt where the ratio η_* may in general be different than η . As already noted earlier, a choice of $\eta_* \leq \eta$ results in a true adiabatic evolution and is expected to yield at the end of the adiabatic process, a state that is very close to the equal superpositions of all solution states.

In addition, the adiabatic process dictates the initial conditions

$$a(s=0) = b(s=0) = 1, \quad (20)$$

which correspond to the fully-symmetric state (i.e., an equal superposition of all possible classical states). The

specific value of 1 chosen here leads to the simple normalization condition

$$\eta|a|^2 + (1 - \eta)|b|^2 = 1, \quad (21)$$

that, similarly to the equations of motion, does not explicitly depend on N or M but only on their ratios.

B. End probabilities

At the end of the evolution, at $s = 1$, the final state of the system is a linear combination of the equal superposition of solutions states, namely, of $|\psi_{\text{sol}}\rangle \propto \sum_{m \in \mathcal{M}} |m\rangle$ and the equal superposition of the non-solution states $|\psi_{\text{no-sol}}\rangle \propto \sum_{m \notin \mathcal{M}} |m\rangle$. The more the evolution is adiabatic, the larger the amplitude of the solution-states superposition will be. While the exact values of the two complex components at $s = 1$ can not be computed analytically, one can obtain an asymptotic solution in two important limits. One is the limit of small ϵ , i.e., when the allowed error in the final state goes to zero. In the $\epsilon \rightarrow 0$ limit, the two equations above fall under the WKB category [23], and have a series solution of the form

$$a(s) = e^{\frac{i}{\epsilon}\sigma(s)} \text{ with } \sigma(s) = \sum_{k=0}^{\infty} (i\epsilon)^k \alpha_k(s) \quad (22)$$

which can directly be plugged into the equations [note that $b(s)$ is a simple linear combination of $a(s)$ and $a'(s)$]. Solving the resulting equations for the growing powers of ϵ term by term, one may calculate the probability to obtain a solution state, i.e., the squared overlap between the final state at $s = 1$ and the optimal solution $|\psi_{\text{sol}}\rangle$:

$$\begin{aligned} P_{\text{sol}} &= |\langle \psi(s=1) | \psi_{\text{sol}} \rangle|^2 \\ &= \lim_{s \rightarrow 1} \frac{\eta |a(s)|^2}{\eta |a(s)|^2 + (1 - \eta) |b(s)|^2}. \end{aligned} \quad (23)$$

Calculation of the above series solution leads to the following asymptotic solution for P_{sol} in the limit of small ϵ :

$$P_{\text{sol}}(\epsilon \rightarrow 0) = 1 - \epsilon^2 \eta (1 - \eta) + O(\epsilon^4). \quad (24)$$

To leading order in ϵ , the probability to find a solution does not depend on value of η_* , as long as one chooses a small enough value for ϵ . As expected, when ϵ goes to 0 (i.e., when no error is allowed), the probability to end up in the equal superposition of solution states approaches 1 (in this case, the running time of the algorithm goes to infinity).

The more interesting limit however, is the one in which ϵ is small but kept fixed while N , the dimension of the Hilbert space (alternatively, the size of the database) goes to infinity. This limit translates to the limit where the ratios $\eta = M/N$ and $\eta_* = M_*/N$ go to zero. Here, we assume that the number of solutions M does not scale with

N . This can be imposed by setting an N -independent upper bound on the number of solutions, M_{max} . (We note that in the case where the number of solutions M scales with N , the Quantum Counting problem becomes less interesting, as the classical probability of finding a solution, $P_{\text{sol}}^{(\text{classical})} = M/N = \eta$, becomes of order unity).

In the limit of $N \rightarrow \infty$, following a careful asymptotic analysis, we obtain for P_{sol} , quite expectedly, the following ‘Landau-Zener type’ probability:

$$P_{\text{sol}}(N \rightarrow \infty) \approx 1 - e^{-\frac{\pi\eta}{4\epsilon\eta_*}} = 1 - e^{-\frac{\pi M}{4\epsilon M_*}}. \quad (25)$$

As expected, the probability of obtaining a solution increases with decreasing ϵ and also, as discussed in the previous section, with decreasing M_* , which is set by the adiabatic profile function. Most importantly, in the $N \rightarrow \infty$ limit, the above probability has a well established N -independent value. The above probability will become useful in what follows when we address the problem of Quantum Counting.

V. QUANTUM COUNTING: ZERO VS NONZERO NUMBER OF SOLUTIONS

Before addressing the full-complexity of the general quantum counting problem, let us first address the special case of finding whether or not the number of solutions M (number of zero entries in the problem Hamiltonian) is zero. Circuit-based algorithms give a running time that is on the order of $O(\sqrt{N})$ [17, 18], that is, a quadratic speedup over the analogous classical algorithm.

A successful adiabatic algorithm may be constructed in the following manner. One runs the QAA algorithm twice: Once with the original problem Hamiltonian of $\hat{H}_p$, Eq. (11), and a second time with $\hat{H}'_p = 1 - \hat{H}_p$. The adiabatic profile function in both cases is chosen to be such that $s(t)$ obeys $ds/dt = \epsilon g^2(\eta = 1/N, s)$, i.e., suitable for efficiently solving the case of any nonzero number of solutions.

Now, if the number of solutions M is zero, then neither of the problem Hamiltonians will have any effect on the state of the system, and the state will remain the initial state $|\phi\rangle$ throughout the adiabatic evolution, except for an undetectable global phase. A measurement of the z -magnetization at the end of the run will produce a random configuration with energy 0 (for $\hat{H}_p$) in one run and energy 1 (for $\hat{H}'_p$) in the other.

If on the other hand the number of solutions is nonzero, the Grover LAE procedure ensures us that at the end of each of the two adiabatic runs, at $s = 1$, the final state of the system will be very close to $|\psi_{\text{sol}}\rangle$, the equal superposition of zero-energy states with a probability greater than $P_{\text{sol}} = 1 - e^{-\frac{\pi M}{4\epsilon}}$ (in the $N \rightarrow \infty$ limit), and a measurement along the z direction will produce a zero-energy state with this probability in both runs.

We conclude then, that two runs of the adiabatic algorithm whose running time is $\mathcal{T} \propto \sqrt{N}$ are sufficient

for establishing whether or not the number of solutions is zero.

VI. QUANTUM COUNTING: THE GENERAL CASE

The general case of estimating M can be formulated based on the probability P_{sol} given in Eq. (25). Let us first briefly analyze the classical analogue of that same problem. In the classical case, a random sampling of items in the database will give $P_{sol}^{(classical)} = M/N = \eta$ for each picked item. The number of successes after k runs will therefore be distributed binomially with the unbiased mean of $\hat{\eta}^{(classical)} = \eta$ and a sampling error of:

$$\Delta \hat{\eta}^{(classical)} \sim \frac{\sqrt{\eta(1-\eta)}}{\sqrt{k}} \approx \frac{\sqrt{\eta}}{\sqrt{k}}. \quad (26)$$

In terms of the number of solutions M , we find that the error in M is

$$\Delta \hat{M}^{(classical)} \sim \frac{\sqrt{MN}}{\sqrt{Nk}}, \quad (27)$$

i.e., for the error to scale as $\sqrt{M}$, the number of trials k required for the search, has to scale linearly with the dimension of the database N .

Going back to the corresponding quantum problem, the question becomes: How many independent runs k of the adiabatic procedure, each run producing a solution-state with probability P_{sol} [as given by Eq. (25)], are necessary to yield an unbiased estimate of M with an error rate that, similarly to the classical case, scales like $\sqrt{M}$? Noting that the probability generated by each adiabatic run, does not depend on the size of the database N (in contrast to the probability in the classical case), a quick calculation analogous to the one done for the classical case above yields:

$$\Delta \hat{M} \sim \frac{4\epsilon M_*}{\pi} \sqrt{\frac{e^{\frac{\pi M}{4\epsilon M_*}} - 1}{k}}. \quad (28)$$

The number of trials needed to yield an error that scales like $\sqrt{M}$ is therefore:

$$k \propto \frac{16\epsilon^2 M_*^2 \left(e^{\frac{\pi M}{4\epsilon M_*}} - 1 \right)}{M\pi^2}. \quad (29)$$

Choosing M_* to be somewhat larger than $M_{\max}$ (for example, 10 times the cutoff value), the exponent above can be approximated by taking only the two leading terms of a Taylor-series expansion, and we end up with the required number of trials $k \propto M_*$.

Note that $\Delta \hat{M}$, while it may depend on M , does not scale with N . The number of trials needed to obtain any desired error is therefore N -independent. Now, the running time of each trial on the other hand scales like

$\sqrt{N/M_*}$ [see Eq. (8)]. The overall running time of the quantum algorithm therefore scales like $\sqrt{N}$ (as M_* does not scale with N) and the algorithm is therefore quadratically faster than its classical analogue.

VII. PHASE DETECTION

The Quantum Counting algorithm outlined above, may also be used to solve phase estimation problems within which one is required to estimate the eigenphases (i.e., the phases of the eigenvalues) of a given unitary matrix. The above quantum counting algorithm may be utilized here in the sense that the (unnormalized) fully-symmetric initial wave function $|\phi\rangle$ may be re-expressed in the form:

$$|\phi\rangle = \sqrt{\eta}|\alpha\rangle + \sqrt{1-\eta}|\beta\rangle, \quad (30)$$

where we have defined:

$$|\alpha\rangle = \frac{1}{\eta} \sum_{m \in \mathcal{M}} |m\rangle, \quad (31)$$

$$|\beta\rangle = \frac{1}{1-\eta} \sum_{m \notin \mathcal{M}} |m\rangle. \quad (32)$$

Replacing $\eta = M/N$ with the appropriate angle of $\sin^2(\theta/2)$ reveals that estimating M is the same as estimating the angle θ for the wave function:

$$|\phi\rangle = \sin(\theta/2)|\alpha\rangle + \cos(\theta/2)|\beta\rangle, \quad (33)$$

meaning that quantum counting may be thought of as a phase estimation algorithm, where the phase here is represented by the angle θ .

VIII. SUMMARY AND CONCLUSIONS

We have given a prescription for solving the Quantum Counting problem in which the number of occurrences M of a specific item within an unsorted database of size N is to be estimated. We have shown that using Local Adiabatic Evolution (LAE) on Grover-type problems, the running time of the algorithm scales like $\sqrt{N}$, i.e., it is quadratically faster than the corresponding classical algorithm and on par with the circuit-based result.

It would be interesting to see whether the algorithm outlined above can be used as the basis for the solution to the more general problem of Quantum Phase Estimation of which the phase detection problem discussed previously may be thought as a special case, and within which one is required to estimate the eigenphase of an eigenvector of a given unitary operator.

The importance of the above results, aside from the implications of having an efficient quantum-adiabatic algorithm for this and related problems, lies in the fact that it is one of very few examples that illustrate the power

and potential that are encompassed in adiabatic quantum computation, providing an adiabatic quantum algorithm that is as efficient as its circuit-model counterpart.

Acknowledgments

We thank Peter Young, Eleanor Rieffel and Jérémie Roland for useful comments and discussions. We ac-

knowledge partial support by the National Security Agency (NSA) under Army Research Office (ARO) contract number W911NF-09-1-0391, and in part by the National Science Foundation under Grant No. DMR-0906366.

-
- [1] E. Farhi, J. Goldstone, S. Gutmann, J. Lapan, A. Lundgren, and D. Preda, *Science* **292**, 472 (2001), a longer version of the paper appeared in arXiv:quant-ph/0104129.
 - [2] L. M. K. Vandersypen, M. Steffen, G. Breyta, C. S. Yannoni, M. H. Sherwood, and I. L. Chuang, *Nature* **414**, 883887 (2001).
 - [3] Z. Bian, F. Chudak, W. G. Macready, L. Clark, and F. Gaitan (2012), (arXiv:1201.1842).
 - [4] T. Hogg, *Phys. Rev. A* **67**, 022314 (2003).
 - [5] E. Farhi, J. Goldstone, and S. Gutmann (2002), (arXiv:quant-ph/0201031).
 - [6] E. Farhi, J. Goldstone, S. Gutmann, and D. Nagaj, *International Journal of Quantum Information* **6**, 503 (2008), (arXiv:quant-ph/0512159).
 - [7] B. Altshuler, H. Krovi, and J. Roland (2009), (arXiv:0908.2782v2).
 - [8] S. Knysh and V. N. Smelyanskiy (2011), (arXiv:1005.3011).
 - [9] A. P. Young, S. Knysh, and V. N. Smelyanskiy, *Phys. Rev. Lett.* **101**, 170503 (2008), (arXiv:0803.3971).
 - [10] A. P. Young, S. Knysh, and V. N. Smelyanskiy, *Phys. Rev. Lett.* **104**, 020502 (2010), (arXiv:0910.1378).
 - [11] I. Hen and A. P. Young, *Phys. Rev. E* **84**, 061152 (2011), arXiv:1109.6872v2.
 - [12] I. Hen, *Phys. Rev. E* **85**, 036705 (2012), arXiv:1112.2269v2.
 - [13] D. Aharonov, W. van Dam, J. Kempe, Z. Landau, S. Lloyd, and O. Regev, *SIAM Journal of Computing* **37**, 166 (2007).
 - [14] A. Mizel, D. A. Lidar, and M. Mitchell, *Phys. Rev. Lett.* **99**, 070502 (2007).
 - [15] J. Roland and N. J. Cerf, *Phys. Rev. A* **65**, 042308 (2002).
 - [16] L. K. Grover, *Phys. Rev. Lett.* **79**, 325 (1997).
 - [17] G. Brassard, P. Hoyer, and A. Tapp, *Automata, Languages and Programming* **1443**, 820 (1998).
 - [18] M. A. Nielsen and I. L. Chuang, *Quantum Computation and Quantum Information* (Cambridge University Press, Cambridge, England, 2000).
 - [19] T. Kato, *J. Phys. Soc. Jap.* **5**, 435 (1951).
 - [20] A. Messiah, *Quantum Mechanics* (North-Holland, Amsterdam, 1962).
 - [21] G. H. Wannier, *Physics* **1**, 251 (1965).
 - [22] J. Roland and N. J. Cerf, *Phys. Rev. A* **68**, 062312 (2003).
 - [23] C. M. Bender and S. A. Orszag, *Advanced Mathematical Methods for Scientists and Engineers* (McGraw-Hill, New York, USA, 1978).